

MD300C13



FINGERTIP PULSE OXIMETER

Pulse oximeter is a very important and common device to check oxygen saturation (SpO₂) and pulse rate. As a small, compact, simple, reliable and durable physiological monitoring device, Fingertip pulse oximeter is widely applied in clinic, hospital, social medical organization, and homecare etc.



FEATURES

- ♥ High brightness LED displays SpO₂, PR, and Pulse bar
- ♥ Low power consumption; battery-low indication
- ♥ Automatically power off; 2pcs AAA-size batteries
- ♥ Two display modes
- ♥ Certifications: CE, FDA



TECHNICAL SPECIFICATIONS

Application Range

Adult, adolescent and child

SpO ₂		Pulse Rate	
Measurement Range:	70%~100%	Measurement Range:	30bpm~250bpm
Resolution:	1%	Resolution:	1bpm
Measurement Accuracy:	70%~100% ±2%; 0%~69% no definition	Measurement Accuracy:	30bpm~99bpm ±2bpm; 100bpm~250bpm ±2%
Display		Dimensions and Weight	
Type:	LED	Dimension:	58mm (L) * 32mm (W) * 34mm (H)
Parameters:	SpO ₂ , PR, Pulse bar	Weight:	50g (including batteries)
Power Requirements			
Battery:	Two AAA-size 1.5V Batteries	Power Consumption:	Less than 40mA
Environment Requirements			
Operation Temperature:	5°C~40°C	Operation Humidity:	15% ~ 93%, no condensation
Storage Temperature:	-25°C~+70°C	Storage Humidity:	≤93%, no condensation

Beijing Choice Electronic Tech Co., Ltd.

Room 4104, No. A12 Yuquan Road, Haidian District,
Beijing 100143, P.R.China
Website: www.choicemed.com Fax: 86 10-88204632
Email: market@choicemed.com Tel: 86 10-88204630/31

ChoiceMMed
Providing a Better Life

NOTE The specifications are subject to changes without prior notice.
Revised Date: 25 January 2019